

5 FEB 65  
TM 11-5820-235-35P

DEPARTMENT OF THE ARMY TECHNICAL MANUAL

EMFO LIBRARY

D 25

DS, GS, AND DEPOT MAINTENANCE  
REPAIR

PARTS AND SPECIAL TOOLS LIST

AMPLIFIER, RADIO FREQUENCY

AM-738/FRT-22, AM-738A/FRT-22,


AM-738B/FRT-22; CONTROL, POWER

SUPPLY C-2446/FRT-22A; POWER

SUPPLIES PP-1089/FRT-22,

PP-1970/FRT-22A; TRANSFORMER, POWER,

STEP-UP TF-197/FRT-22



HEADQUARTERS, DEPARTMENT OF THE ARMY

17 NOVEMBER 1964

43/



TECHNICAL MANUAL

No. 11-5820-235-35P

HEADQUARTERS,  
DEPARTMENT OF THE ARMY  
WASHINGTON, D. C. 20315, 17 November 1964

**AMPLIFIER, RADIO FREQUENCY AM-738/FRT-22,  
AM 738A/FRT 22, AM 738B/FRT 22; CONTROL, POWER  
SUPPLY C-2446/FRT-22A; POWER SUPPLIES  
PP-1089/FRT-22, PP-1970/FRT-22A;  
TRANSFORMER, POWER, STEP-UP TF-197/FRT-22**

	Paragraph	Page
SECTION I. INTRODUCTION		
Scope -----	1	3
Parts for maintenance -----	2	3
Maintenance allowances -----	3	4
Requisitioning information -----	4	4
References -----	5	4
Reporting of equipment manual improvements -----	6	5
II. FUNCTIONAL PARTS LISTS -----		7

\*This manual, together with C9, 17 November 1964, of TM 11-847, 18 February 1955, and TM 11-5820-280-20P, 17 November 1964, supersedes TM 11-5820-235-15P, 28 November 1958.

1000

RECEIVED  
JAN 10 1960  
FEDERAL BUREAU OF INVESTIGATION  
U. S. DEPARTMENT OF JUSTICE

TO : DIRECTOR, FBI  
FROM : SAC, NEW YORK  
SUBJECT: [Illegible]

- 1. [Illegible]
- 2. [Illegible]
- 3. [Illegible]
- 4. [Illegible]
- 5. [Illegible]
- 6. [Illegible]
- 7. [Illegible]
- 8. [Illegible]
- 9. [Illegible]
- 10. [Illegible]



## SECTION I INTRODUCTION

### 1. Scope

a. This manual lists the quantities of repair parts for direct support, general support, and depot maintenance and is a basis for requisitioning authorized parts. It is also a guide for depot maintenance in establishing initial levels of spare parts.

b. Columns are as follows:

- (1) *Source, maintenance, and recoverability code.* Source, maintenance, and recoverability codes indicate the technical service responsible for supply, the maintenance category at which an item is stocked, categories at which an item is installed or repaired, and whether an item is repairable or salvageable. The source code column is divided into four parts.

(a) *Column A.* This column indicates the materiel code and designates the area of responsibility for supply. AR 310-1 defines the basic numbers used to identify the materiel code. If the part is Signal materiel responsibility, the column is left blank.

(c) *Column C.* This column indicates the lowest maintenance category authorized to install the part.

"O"—Organizational maintenance (operator and organization).

"F"—Direct support maintenance.

(d) *Column D.* Not used.

(2) *Federal stock number.* This column lists the 11-digit Federal stock number.

(3) *Designation by model.* The dagger (+) indicates model in which the part is used.

(4) *Description.* Nomenclature or the standard item name and brief identifying data for each item are listed in this column. When requisitioning, enter the nomenclature and description.

(5) *Unit of issue.* The unit of issue is

each unless otherwise indicated and is the supply term by which the individual item is counted for procurement, storage, requisitioning, allowances, and issue purposes.

(6) *Expendability.* Nonexpendable items are indicated by NX. Expendable items are not annotated.

(7) *Quantity incorporated in unit.* This column lists the quantity of each part found in a given assembly, component, or equipment.

(8) *Direct support.* This column indicates quantities of repair parts authorized for initial stockage for use in the direct support maintenance and in supply support to organization. The quantities are based on 100 equipments to be maintained for a 15-day period.

(9) *General support.* The numbers in this column indicate quantities of repair parts authorized for initial stockage for use in general support maintenance. The quantities are based on 100 equipments to be maintained for a 15-day period.

(10) *Depot.* The numbers in this column indicate quantities of repair parts authorized for depot maintenance and for initial stockage for maintenance, and for supply support to lower categories. The entries are based on the quantity required for rebuild of 100 equipments.

(11) *Illustration.* The "Item No." column lists the reference symbols used for identification of the items in the illustration or text of the manual.

### 2. Parts for Maintenance

When this equipment is used by signal service organizations organic to the theater headquarters or communication zones to provide theater communications, those repair parts authorized up to and including general support

are authorized for stockage by the organization operating this equipment.

### 3. Maintenance Allowances

"AR" appearing in maintenance allowance columns indicates that the item may be requisitioned "as required;" however, estimated minimum quantities may be stocked to cover immediate needs. This symbol applies to common hardware and bulk materials only.

### 4. Requisitioning Information

a. The allowance factors are based on 100 equipments. In order to determine the number of parts authorized for initial stockage for the specific number of equipments supported, the following formula will be used and carried out to two decimal places.

Specific number of equipments supported

$$\times \frac{\text{allowance factor}}{100} =$$

Number of parts authorized for  
initial stockage.

b. Fractional values obtained from above computation will be rounded to whole numbers as follows:

- (1) When the total number of parts authorized is less than 0.5, the quantity authorized will be zero.
- (2) When the total number of parts authorized is between 0.5 and 1.0, the quantity authorized will be one.
- (3) For all values above one, fractional values below 0.5 will revert to the next lower whole number and fractional value 0.5 and above will advance to the next higher whole number.

c. The quantities determined in accordance with the above computation represent the initial stockage for a 15-day period.

### 5. References

A maintenance allocation chart and basic issue items are contained in TM 11-846 & TM 11-846 & TM 11-847. Additional instructions concerning maintenance of this equipment are contained in:

Operator's Maintenance Repair Parts and Special Tools List:

TM 11-5820-212-10P, Frequency Shift Keyer KY-45/FRT-5.

TM 11-5820-331-10P, Oscillator, Radio Frequency 0-243A/FRT-24.

TM 11-5820-332-10P, Radio Frequency Oscillator 0-91/FRT-5.

Organizational Maintenance Repair Parts and Special Tools List:

TM 11-5820-280-20P, Transmitting Sets, Radio AN/FRT-22, AN/FRT-22A, AN/FRT-26, AN/FRT-26A, and AN/FRT-26B.

Organizational Maintenance Repair Parts and Special Tools List and Maintenance Allocation Chart:

TM 11-5820-212-20P, Frequency Shift Keyer KY-45/FRT-5.

TM 11-5820-331-20P, Oscillator, Radio Frequency 0-243A/FRT-24.

TM 11-5820-332-20P, Radio Frequency Oscillator 0-91/FRT-5.

Operator's and Organizational Maintenance Repair Parts and Special Tools List and Maintenance Allocation Chart:

TM 11-5820-354-12P, Power Supply PP-454/FRT-5.

Field and Depot Maintenance Repair Parts and Special Tools List:

TM 11-5820-212-35P, Frequency Shift Keyer KY-45/FRT-5.

TM 11-5820-331-35P Oscillator, Radio Frequency 0-243A/FRT-24.

TM 11-5820-332-35P, Radio Frequency Oscillator 0-91/FRT-5.

TM 11-5820-354-35P, Power Supply PP-454/FRT-5.

TM 11-5820-213-35P, Transmitters, Radio T-454/FRT-26, T-454A/FRT-26, Control, Power Supply C-1402/FRT-26, Oscillator, Radio Frequency 0-270/FRT-26, Power Supply Control C-2447/FRT-26B, Power Supply Assembly PP-1088/FRT-26 and Power Supply PP-1971/FRT-26B.



## **6. Reporting of Equipment Manual Improvements**

The direct reporting by the individual user of errors, omissions, and recommendations for improving equipment is authorized and encouraged. DA Form 2028 will be used for reporting these improvements. This form may be completed by using pencil, pen, or typewriter.

DA Form 2028 will be completed in triplicate and forwarded by the individual using the manual. The original and one copy will be forwarded directly to: Commanding General, U. S. Army Electronics Command, ATTN: AMSEL-MR-MA, Fort Monmouth, New Jersey 07703. One information copy will be furnished to the individual's immediate supervisor (officer, noncommissioned officer, supervisor, etc).

## SECTION II. FUNCTIONAL PARTS LIST

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
F	6625-668-9179	+	+		NX	1	1.0	0.5	3.0		M1501
F	6625-668-5103	+	+			1	1.0	0.5	3.0		
F	5820-561-6305	+	+			2	1.0	0.5	6.0		E1599.37
F	3110-156-4652	+	+			3	1.0	0.5	6.0		01586
F	3110-155-9601	+	+			9	1.7	0.9	18.0		01599.36
F	3110-156-4663	+	+			14	2.1	1.1	28.0		01599-37
F	3110-155-8416	+	+			1	1.0	0.5	2.0		01599.56
F	3110-198-2242	+	+			4	1.0	0.5	8.0		01571
F	3110-155-9628	+	+			2	1.0	0.5	4.0		0706,0707
F	3130-227-2922	+	+			2	1.0	0.5	4.0		B1501C
F	3110-112-5768	+	+			6	1.3	0.7	12.0		01589
F	5820-569-6568	+	+			1	1.0	0.5	2.0		01553

SELM's Form  
1 Jun 64

1155 (Successes SELM's 003 TF, which is obsolete)

AM-738/FRT-22



SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
			AM-738/FRT-22 (continued)								
	3030-235-7699	+	BELT: Browning FHP132; Collins part/dwg #233-0025-00			2	1.0	0.5	80.0		B1501A ALT.
	3030-060-0446	+	BELT, V: Peerless Elect #SL-370 (NOTE: for blower B-1501)			2	1.0	0.5	80.0		
	3030-180-2081	+	BELT: Browning 4L360; Collins part/dwg #233-0043-00			2	1.0	0.5	80.0		O1501A
F	5306-639-8995	+	BOLT, EXTERNALLY RELIEVED BODY; Collins part/dwg #504-1501-001			8	1.5	0.8	24.0		H1599-93
F	5820-393-1226	+	BRACKET: Collins part/dwg #505-1680-00			12	1.9	1.0	24.0		
F	5820-547-9187	+	BRAKE, SHOE TYPE: Collins part/dwg #505-7519-002			3	1.0	0.5	9.0		0702, 01599-48
F	6145-846-7697		CABLE, HIGH VOLTAGE: 15,000-volt high-tension, high-temperature cable				R	R			
F	5950-642-5516	+	CAM, ELECTRICAL: Collins part/dwg #504-4828-003			6	1.3	0.7	30.0		O1529D
F	5950-192-4513	+	CAM, ELECTRICAL: Collins part/dwg #504-4874-002			6	1.3	0.7	30.0		O1529E
O	5920-244-5150	+	CAP, ELECTRICAL: Bussman: HKP-JQRZ; Collins part/dwg #265-1049-00			2	1.0	0.5	6.0		XF1501A XF1502A
F	5910-667-6112	+	CAPACITOR, FIXED, CERAMIC DIELECTRIC; Centralab #850-001			4	1.0	0.5	12.0		C1599.1 thru C1599.4
F	5910-649-3182	+	CAPACITOR, FIXED, CERAMIC DIELECTRIC; Centralab #850A			2	1.0	0.5	6.0		C1310
F	5910-196-0540	+	CAPACITOR, FIXED, CERAMIC DIELECTRIC; Centralab #858; Collins part/dwg #913-0806-00; Item Nos. C1503 thru C1514, C1557 thru C1584			52	4.5	2.7	156.0		See desc column
F	5910-191-2734	+	CAPACITOR, FIXED, MICA DIELECTRIC; MIL type CM50B472M			4	1.0	0.5	12.0		C1302, C1306 (2 ea)

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
			AM-738/FRT-22 (continued)								
			CAPACITOR, FIXED, MICA DIELECTRIC: MIL type CW35B472M			1	1.0	0.5	3.0		C1501
			CAPACITOR, FIXED, MICA DIELECTRIC: MIL type CW45B103M			2	1.0	0.5	6.0		C1596 C1597
			CAPACITOR, FIXED, MICA DIELECTRIC: MIL type CW50B223M			4	1.0	0.5	12.0		C1534 thru C1537
			CAPACITOR, FIXED, PAPER DIELECTRIC: MIL type CP53B1EF104M			1	1.0	0.5	3.0		C1540
			CAPACITOR, FIXED, PAPER DIELECTRIC: MIL type CP54B1EF254K			6	1.3	0.7	18.0		C803, C804 (3 ea)
			CAPACITOR, FIXED, PAPER DIELECTRIC: MIL type CP53B1FF504K			4	1.0	0.5	12.0		C805 (3 ea), C901
			CAPACITOR, FIXED, PAPER DIELECTRIC: MIL type CP61B1EF105K Item Nos. C705, C801 (3 ea), C802 (3 ea), C1591, C1594, C1595			10	1.7	0.9	30.0		See desc column
			CAPACITOR, FIXED, PAPER DIELECTRIC: Sangamo #62A			2	1.0	0.5	6.0		C1541, C1598
			CAPACITOR, FIXED, PAPER DIELECTRIC: Gudeman #SCB8236B			1	1.0	0.5	3.0		C703
			CAPACITOR, FIXED, PAPER DIELECTRIC: Solar #ALXC.3-4.0 Item Nos. C701, C1550, C1551, C1590, C1592			5	1.3	0.7	15.0		See desc column
			CAPACITOR, FIXED, VACUUM DIELECTRIC: Jennings Rad #W; Collins part/dwg #919-0036-00			4	1.0	0.5	12.0		C1301, C1305 (2 ea)
			CAPACITOR, FIXED, VACUUM DIELECTRIC: Jennings #VCC; Collins part/dwg #919-0101-00			2	1.0	0.5	6.0		C1538, C1539
			CAPACITOR, FIXED, VACUUM DIELECTRIC: Elmac #VC; Collins part/dwg #919-0005-00			3	1.0	0.5	9.0		C1525, C1526, C1587
			CAPACITOR, FIXED, VACUUM DIELECTRIC: Jennings #VCC; Collins part/dwg #919-0100-00			1	1.0	0.5	3.0		C1587

SELMS Form 1 Jun 64 1155 (Supersedes SELMS 003 TF, which is obsolete)

AM-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
F	5910-667-6729	+	AM-738/FRT-22 (continued) CAPACITOR, AIR DIELECTRIC: All Star Prod Inc.#GT3; Collins part/dwg #922-0246-00			2	1.0	0.5	6.0		CL309 (2 ea)
F	5910-186-1664	+	CAPACITOR, VARIABLE, AIR DIELECTRIC: Hammarlund #TC-900-K; Collins part/dwg #920-0073-00			2	1.0	0.5	6.0		CL585, CL586
F	5910-666-7425	+	CAPACITOR, VARIABLE, VACUUM DIELECTRIC Jennings #UXG; Collins part/dwg #919-0092-00			3	1.0	0.5	9.0		CL530A, CL531A, CL532A
F	5935-223-0575	+	CLAMP, ELECTRICAL: Amphenol #AN-3057-8			3	1.0	0.5	9.0		PL503A PL504A
F	5920-309-5185	+	CLIP, ELECTRICAL: Multi Elec, #2026-3; Collins part/dwg #265-1015-00			4	1.0	0.5	12.0		EL535
F	5940-279-1297	+	CLIP, ELECTRICAL: Multi-Elec #2022J; Collins part/dwg #265-1001-00			14	2.1	1.1	51.0		EL536 thru EL536.12
F	5940-204-5233	+	CLIP, ELECTRICAL: Multi Elec #2020J; Collins part/dwg #265-5010-00			12	1.9	1.0	36.0		EL537
F	5920-852-9086	+	CLIP, ELECTRICAL: Bussman #4464			2	1.0	0.5	6.0		EL538.1 EL538.2
F	5820-312-0206	+	CLIP, ELECTRICAL: Collins part/dwg #504-5617-002			6	1.3	0.7	18.0		XV1501K thru XV1506K
F	5950-387-1275	+	COIL, RADIO FREQUENCY: Collins part/dwg #504-1023-003			2	1.0	0.5	6.0		L1501, L1502
F	5950-387-1234	+	COIL, RADIO FREQUENCY: Collins part/dwg #504-1883-004			1	1.0	0.5	3.0		L1505
F	5950-387-1228	+	COIL, RADIO FREQUENCY: Collins part/dwg #357-4006-00			1	1.0	0.5	3.0		L1506
F	5950-219-9806	+	COIL, RADIO FREQUENCY: Collins part/dwg #504-5291-002			2	1.0	0.5	6.0		L1510AB L1511AB
F	5950-333-6238	+	COIL, RADIO FREQUENCY: Collins part/dwg #504-1825-003			1	1.0	0.5	3.0		L1507

SELM Form  
1 Jun 64

1155 (Source: SELMS 03 TP, which is obsolete)

AM-738/FRT-22



SOURCE CODE	FEDERAL STOCK NUMBER				DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPT	ILLUSTRATION	
													FIGURE NO.	ITEM NO.
A	B	C	D											
F						AM-738/FRT-22 (continued)			1	1.0	0.5	3.0		L1508
						COIL, RADIO FREQUENCY: Collins part/dwg #504-1826-003								
F						COIL, RADIO FREQUENCY: Collins part/dwg #504-5228-003			1	1.0	0.5	3.0		L1509
F						COIL, RADIO FREQUENCY: Collins part/dwg #506-7154-002			2	1.0	0.5	6.0		L1515 L1516
F						COIL, RADIO FREQUENCY: Collins part/dwg #507-9703-002			2	1.0	0.5	6.0		L1517 L1518
F						CONNECTOR, PLUG, ELECTRICAL: Cannon Elec #IK-30-23C-1 1/8			1	1.0	0.5	6.0		PI501
F						CONNECTOR, PLUG, ELECTRICAL: Cannon Elec #RIK-30-24C-1-1/8			1	1.0	0.5	3.0		PI502
F						CONNECTOR, PLUG, ELECTRICAL: ANA #AN-3106A-16S-1S			2	1.0	0.5	6.0		PI503 PI504
F						CONNECTOR, PLUG, ELECTRICAL: Cannon Elec #DK-9-21C-5/8			1	1.0	0.5	3.0		PI507
F						CONNECTOR, PLUG, ELECTRICAL: Cinch #14619; Item Nos. PI508 thru PI514			7	1.5	0.8			See desc column
F						CONNECTOR, RECEPTACLE, ELECTRICAL: Rhoden Mfg Co. #502B; Collins part/dwg #190-01103-00			12	1.9	1.0	36.0		E808 thru E811
F						CONNECTOR, RECEPTACLE, ELECTRICAL: Jones HB-#SS-10-AB-1/16			3	1.0	0.5	9.0		J807 J808 J809
F						CONNECTOR, RECEPTACLE, ELECTRICAL: Cannon Elec #IK-30-32S			1	1.0	0.5	3.0		JI501
F						CONNECTOR, RECEPTACLE, ELECTRICAL: Cannon Elec #RIK-30-31SL			1	1.0	0.5	3.0		JI502
F						CONNECTOR, RECEPTACLE, ELECTRICAL: Collins part/dwg #357-3007-00			2	1.0	0.5	6.0		J701, JI504
F						CONNECTOR, RECEPTACLE, ELECTRICAL: Cannon Elec #DPP-45-33G-1			2	1.0	0.5	6.0		JI505 PI506
F						CONNECTOR, RECEPTACLE, ELECTRICAL: Cannon Elec #DPD-H5-34P			2	1.0	0.5	6.0		PI505 JI506

SELMs Pam  
1 Jun 64

1155 (Replaces SELMS 003 TP, which is obsolete)

AM-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER				DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
	A	B	C	D								FIGURE NO.	ITEM NO.
						AM-738/FRT-22 (continued)							
F					5935-283-7103	+ + +	CONNECTOR, RECEPTACLE: Cannon Elec #GK-9-32SL		1	1.0	0.5	3.0	J1507
F					5935-283-7106	+ + +	CONNECTOR, RECEPTACLE, ELECTRICAL: Jones HB- #P-10-AB-1/16		3	1.0	0.5	9.0	P801
F					5820-577-7001	+ + +	CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #543-0299-002		12	1.9	1.0	24.0	01526
F					5820-378-5265	+ + +	CONTACT, COIL: Collins part/dwg #504-3611-001		12	1.9	1.0	24.0	01529C
F					5950-192-4508	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-1483-001		8	1.5	0.8	24.0	01563
F					5950-192-4573	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-3613-002		16	2.3	1.2	48.0	01526
F					5820-561-0875	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #503-9057-00		6	1.3	0.7	18.0	E1590
F					5820-561-0873	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-1502-001		6	1.3	0.7	18.0	E1591
F					5950-192-4567	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-1750-002		2	1.0	0.5	6.0	01525
F					5950-196-0383	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-6571-002		4	1.0	0.5	12.0	01527
F					5935-259-9767	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-6572-00		4	1.0	0.5	12.0	01528
F					5950-196-0388	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-5631-00		12	2.1	1.1	36.0	01529A
F					5950-192-4554	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-3621-002		24	2.6	1.4	72.0	01529B
F					5950-192-4562	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-4819-002		1	1.0	0.5	3.0	01530
F					5935-537-4365	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-3620-002		12	1.9	1.0	36.0	01561
F					5820-570-5530	+ + +	CONTACT, ELECTRICAL: Collins part/dwg #504-8572-002		8	1.5	0.8	24.0	01562

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
F	5820-590-7962	+	+	AM-738/PRT-22 (continued)		18	2.5	1.3	54.0		See desc column
				CONTACT, ELECTRICAL: Collins part/dwg #542-4451-002 Item Nos. XV1501D thru XV1506D							
F	5820-590-7963	+	+	CONTACT, ELECTRICAL: Collins part/dwg #542-4450-002		12	1.9	1.0	36.0		XV1501E thru XV1506E
F	5935-346-5954	+	+	CONTACT, ELECTRICAL: Collins part/dwg #504-1523-001		6	1.3	0.7	18.0		XV1501F thru XV1506F
F	5820-502-9416	+	+	CONTACT, ELECTRICAL: Collins part/dwg #505-4438-002		48	3.4	1.9	144.0		XV1501L thru XV1506L
F	5820-502-9417	+	+	CONTACT, ELECTRICAL: Collins part/dwg #505-4439-002		48	3.4	1.9	144.0		XV1501M thru XV1506M
F	5960-219-6222	+	+	CONTACT, ELECTRICAL: Collins part/dwg 506-9704-002		6	1.3	0.7	18.0		XV1501R thru XV1506R
F	5820-547-9143	+	+	COUPLING, COIL: Collins part/dwg #504-1803-003		2	1.0	0.5	6.0		01599.96
F	5820-605-0778	+	+	COUPLING, SHAFT, FLEXIBLE: Collins part/dwg #503-9084-002		3	1.0	0.5	18.0		01554
F	5355-677-6337	+	+	DIAL: Helipot Corp #SR-100		30	3.4	1.9	60.0		E1577
F	5820-561-6306	+	+	DRIVE, TUNING: Collins part/dwg #504-1081-004		1	1.0	0.5	3.0		Z1510
F	5820-547-9146	+	+	DRUM ASSEMBLY: Collins part/dwg #504-1810-003		1	1.0	0.5	3.0		A1599.35
F	5820-547-9147	+	+	DRUM ASSEMBLY: Collins part/dwg #504-1828-003		1	1.0	0.5	3.0		A1599.36
F	5820-547-9144	+	+	DRUM ASSEMBLY: Collins part/dwg #504-1806-003		1	1.0	0.5	3.0		A1599.82
F	5820-547-9145	+	+	DRUM ASSEMBLY: Collins part/dwg #504-1807-003		1	1.0	0.5	3.0		A1599.83
F	5820-392-5783	+	+	DRUM, BRAKE: Collins part/dwg #505-7511-002 Item Nos. 0711, 01565, 01567		3	1.0	0.5	6.0		See desc column

SELMS Form 1155 (Supersedes SELMS 03 TF, which is obsolete)  
1 Jun 64

AM-738/PRT-22



SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
	5960-166-7664	+	+	+		3	25.4	13.2	300.0		V801
	5960-166-7663	+	+	+		3	25.4	13.2	300.0		V802
	5960-188-0880	+	+	+		4	35.2	17.6	400.0		V1301 V1303
	5960-230-5298	+	+	+		6	52.8	26.4	600.0		V1501 thru V1506
	5960-188-6593	+	+	+		1	21.9	11.0	100.0		V1507
F	4140-542-3241		+			1	1.0	0.5	1.0		B1501
F	4130-274-8290	+	+	+		2	1.0	0.5	6.0		O1587
O	5920-199-9498	+	+	+		1	1.0	0.5	50.0		
O	5920-284-9220	+	+	+		1	1.0	0.5	50.0		
F	5920-570-5117	+	+	+		2	1.0	0.5	6.0		XF1501 XF1502
F	5820-562-8876	+	+	+		2	1.0	0.5	6.0		O1573 O1575
F	5820-547-9154	+	+	+		1	1.0	0.5	3.0		O1533
F	5820-399-7346	+	+	+		1	1.0	0.5	3.0		0725
F	5820-399-7345	+	+	+		1	1.0	0.5	3.0		0726
F	5820-547-9142	+	+	+		1	1.0	0.5	3.0		0704
F	5820-561-0866	+	+	+		1	1.0	0.5	3.0		0705
F	5820-378-5376	+	+	+		2	1.0	0.5	6.0		O1522 O1523
F	5820-561-0877	+	+	+		1	1.0	0.5	3.0		0727

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
P	5820-561-0876	+	+	AM-738/FRT-22 (continued)		1	1.0	0.5	3.0		01518
P	5820-310-4475	+	+	GEAR, SPUR: Collins part/dwg #504-4665-002		2	1.0	0.5	6.0		01519 01520
P	5820-332-5002	+	+	GEAR, SPUR: Collins part/dwg 504-4661-00		1	1.0	0.5	3.0		01521
P	5820-378-5378	+	+	GEAR, SPUR: Collins part/dwg #504-4642-001		1	1.0	0.5	3.0		01532
P	3020-242-9387	+	+	GEAR, SPUR: Collins part/dwg #504-1566-001		1	1.0	0.5	3.0		01537
P	5820-562-8875	+	+	GEAR, SPUR: Collins part/dwg #504-1798-003		1	1.0	0.5	3.0		
P	5820-547-9173	+	+	GEAR, SPUR: Collins part/dwg #506-7662-002		1	1.0	0.5	3.0		01574
P	5820-547-9176	+	+	GEAR, SPUR: Collins part/dwg #506-7659-002		1	1.0	0.5	3.0		01576
P	5820-561-6308	+	+	GEAR, SPUR: Collins part/dwg #506-7667-002		2	1.0	0.5	6.0		01599.87 01599.88
P	5820-640-4538	+	+	GEAR, SPUR: Collins part/dwg #506-7646-002		2	1.0	0.5	6.0		01513 01514
P	5820-333-9705	+	+	GEAR, SPUR: Collins part/dwg #504-4668-002		1	1.0	0.5	3.0		01535
P	5820-310-4742	+	+	GEAR, SPUR: Collins part/dwg #504-1699-002		1	1.0	0.5	3.0		01512
P	5820-562-8877	+	+	GEAR, SPUR: Collins part/dwg #504-4667-002		2	1.0	0.5	6.0		01579 01580
P	5325-489-3075	+	+	GEAR, WORM: Collins part/dwg #506-7649-002		4	1.3	0.7	16.0		E1599.60
P	5960-613-1757	+	+	GROMMET, RUBBER: Continental Rubber #3235		1	1.0	0.5	3.0		
P	5935-651-2698	+	+	HEAT DISSIPATOR: Collins part/dwg #541-6532-00		6	1.3	0.7	18.0		E823, E824
P		+	+	HEAT DISSIPATOR: Collins part/dwg #541-6533-00							

SELMAS Form 1155 (Supersedes SELMAS 003 TF, which is obsolete)  
1 Jun 64

AM-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
									FIGURE NO.	ITEM NO.
A181C D			AM-738/FRT-22 (continued)							
F	4720-547-9198	+	HOSE, RUBBER: Collins part/dwg #506-9715-002		2	1.0	0.5	4.0	A1599 140	
F	5970-144-1599	+	INSULATOR, BOWL: MIL type NS4W4601		2	1.0	0.5	6.0	E1523	
F	5970-538-7926	+	INSULATOR, DISK: Collins part/dwg #504-1698-002		2	1.0	0.5	6.0	E1599.52	
F	5970-538-7916	+	INSULATOR, PLATE: Collins part/dwg #504-1698-002		2	1.0	0.5	6.0	E1598	
F	5970-538-7918	+	INSULATOR, PLATE: Collins part/dwg #504-1748-002		2	1.0	0.5	6.0	E1599	
F	5970-538-7919	+	INSULATOR, PLATE: Collins part/dwg #504-1749-002		1	1.0	0.5	3.0		
O	5970-538-7917	+	INSULATOR, PLATE: Collins part/dwg #504-1831-003		1	1.0	0.5	3.0	E1599.2	
F	5970-519-8416	+	INSULATOR, PLATE: Collins part/dwg #504-4448-001		2	1.0	0.5	6.0	E1599.7	
F	5970-538-7927	+	INSULATOR, PLATE: Collins part/dwg #504-1715-002		1	1.0	0.5	3.0	E1599.13	
F	5970-519-6046	+	INSULATOR, PLATE: Collins part/dwg #504-1716-002		2	1.0	0.5	6.0	E1599.14	
F	5970-519-6047	+	INSULATOR, PLATE: Collins part/dwg #504-1717-002		2	1.0	0.5	6.0	E1599.15	
F	5970-538-7921	+	INSULATOR, PLATE: Collins part/dwg #506-7338-002		1	1.0	0.5	3.0	E1599.22	
F	5970-519-6045	+	INSULATOR, PLATE: Collins part/dwg #504-1764-002		1	1.0	0.5	3.0	E1599.27	
F	5970-538-7922	+	INSULATOR, PLATE: Collins part/dwg #504-5236-002		2	1.0	0.5	6.0	E1599.39	
F	5970-519-6163	+	INSULATOR, PLATE: Collins part/dwg #506-7149-002		2	1.0	0.5	6.0	E1599.46	
F	5970-117-5320	+	INSULATOR, STANDOFF: MIL type #NS4W4616		2	1.0	0.5	6.0	E1513. E1543	



SOURCE CODE	FEDERAL STOCK NUMBER			DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
	A	B	C	D								FIGURE NO.	ITEM NO.
P					AM-738/FRT-22 (continued)			14	2.1	1.1	42.0		See desc column
					INSULATOR, STANDOFF: MIL type #NS4W0316 Item Nos. E1518, E1519.1 thru E1519.5								
P					INSULATOR, STANDOFF: MIL type NS4W0624			4	1.0	0.5	12.0		E1525
P					INSULATOR, STANDOFF: MIL type NS4W0632			2	1.0	0.5	6.0		E1526, E1533
P					INSULATOR, STANDOFF: MIL type NS4W0332			2	1.0	0.5	6.0		E1527
P					INSULATOR, STANDOFF: MIL type NS4W0320			2	1.0	0.5	6.0		E1528
P					INSULATOR, STANDOFF: MIL type NS4W0308			14	2.1	1.1			E1530
P					INSULATOR, STANDOFF: MIL type NS4W0106			4	1.0	0.5	12.0		E1545
P					INSULATOR, STANDOFF: MIL type NS4W0420			3	1.0	0.5	9.0		E1546
P					INSULATOR, STANDOFF: Collins part/dwg #190-1144-00 Item Nos. E1563.1 thru E1563.4			4	1.0	0.5	12.0		See desc column
P					INSULATOR, STANDOFF: MIL type NS4W0208			1	1.0	0.5	3.0		E1576
P					INSULATOR, STANDOFF: Collins part/dwg #504-1817-003			4	1.0	0.5	12.0		E1599.29
P					INSULATOR, STANDOFF: Collins part/dwg #504-1818-003			2	1.0	0.5	6.0		E1599.30
P					INSULATOR, STANDOFF: MIL type NS4W0540			4	1.0	0.5	12.0		E1529
P					INSULATOR, WASHER: Collins part/dwg #506-9706-002			72	5.7	3.5	72.0		C1515E, C1516E
O					KNOB: Collins part/dwg #506-8714-002			10	1.7	0.9	30.0		E1578
O					LAMP, GLOW: GE- #NE-2 Item Nos. I801, I802 (3 ea)			6	1.9	1.0	300.0		See desc column

SELM Form  
1 Jun 64

Army-Ft. Monmouth, NJ 400N 1950-64

AM-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER				DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
	A	B	C	D								FIGURE NO.	ITEM NO.
F						AM-738/FRT-22 (continued)							
F	6240-313-8980	+	+	+		LAMP, GLOW: Littelfuse #201001 Item Nos. I901, I1509, I1518		3	1.3	0.7	150.0		See desc column
O	6240-143-3060	+	+	+		LAMP, INCANDESCENT: Collins part/dwg #262-0041-00 Item Nos. I1501 thru I1508		8	2.3	1.2	400.0		See desc column
O	6240-155-8706	+	+	+		LAMP, INCANDESCENT: GE #47 Item Nos. I1510.1 thru I1510.10		10	2.6	1.4	500.0		See desc column
O	6240-155-7857	+	+	+		LAMP, INCANDESCENT: GE #328 Item Nos. I1511.1 thru I1511.10, I1512.1 thru I1512.10, I1513.1 thru I1513.10, I1514.1 thru I1514.10, I1515.1 thru I1515.10, I1516.1 thru I1516.10		60	8.2	5.3	3000.0		See desc column
F	6250-270-4260	+	+	+		LAMPHOLDER: Dialco 9-S-4634-L Collins part/dwg #262-0042-00		4	1.0	0.5	12.0		XI1501 thru XI1504
F	5995-519-0104	+	+	+		LEAD, ELECTRICAL: Collins part/dwg #504-1603-001		12	1.9	1.0	24.0		El599.35
F	6210-270-4115	+	+	+		LENS, INDICATOR LIGHT: Drake Mfg Co. #25, Collins part/dwg #262-2160-00		10	1.7	0.9	50.0		XI1510.1A thru XI1510.DA
F	6210-299-3908	+	+	+		LENS, INDICATOR LIGHT: Collins part/dwg #262-0106-00		2	1.0	0.5	10.0		XI1505A, XI1508A
F	6210-299-3880	+	+	+		LENS, INDICATOR LIGHT: Collins part/dwg #262-0105-00		1	1.0	0.5	5.0		XI1506A
F	6210-299-3882	+	+	+		LENS, INDICATOR LIGHT: Collins part/dwg #262-0104-00		1	1.0	0.5	5.0		XI1507A
F	6210-299-6381	+	+	+		LIGHT, INDICATOR: Dialco #51702-67 Item Nos. XI1505 thru XI1508		4	1.0	0.5	20.0		See desc column
F	6210-228-5735	+	+	+		LIGHT, INDICATOR: Drake #225A Item Nos. XI1510.1 thru XI1510.10		10	1.7	0.9	50.0		See desc column
O	5820-392-5830	+	+	+		MAINTENANCE PART KIT: Collins part/dwg #233-0038-00		2	1.0	0.5	2.0		Ol510A Ol544A
O	5820-392-5829	+	+	+		MAINTENANCE PARTS KIT: Collins part/dwg #233-0033-00		1	1.0	0.5	1.0		Ol551A

SELMS Form 1 Jun 64 1155 (Replaces SELMS 003 TF, which is obsolete)

AW-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
F	6625-538-9008	+	+		NX	1	1.0	0.5	3.0		M1502
F	6625-668-9406	+	+		NX	1	1.0	0.5	3.0		M1504
F	6105-635-9477	+	+		NX	1	1.0	0.5	2.0		B701B
F	6105-643-4665	+	+		NX	1	1.0	0.5	2.0		B1501B
F	6105-635-9473	+	+		NX	3	1.0	0.5	6.0		See desc column
F	6105-295-0875	+	+		NX	2	1.0	0.5	4.0		B1504 B1505
F	5310-639-8231	+	+			6	1.3	0.7	18.0		See desc column
F	5820-561-6307	+	+			2	1.0	0.5	4.0		EL599.2
F	6130-199-9518	+	+			6	1.3	0.7	18.0		CR801 CR802
F	6130-643-4508	+	+			1	1.0	0.5	3.0		CR1501
F	6130-330-9849	+	+			2	1.0	0.5	6.0		CR1501 CR1503
F	5945-539-3971	+	+			1	1.0	0.5	3.0		K702
F	5945-537-4621	+	+			6	1.3	0.7	18.0		K801, K802
F	5945-521-0211	+	+			1	1.0	0.5	3.0		K1502
F	5945-283-6605	+	+			2	1.0	0.5	6.0		K1503 K1507
F	5945-283-8748	+	+			1	1.0	0.5	3.0		K1504

SELAS Form  
1 Jun 64

Army-Ft. Monmouth, NJ-MON 1556-4

1155  
(Successor SELAS 003 TP, which is obsolete)

AM-738/FRT-22



SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A B C D			AM-738/FRT-22 (continued)								
F	5945-503-5235	+	RELAY, ARMATURE: Collins part/dwg #970-1712-002			1	1.0	0.5	3.0		K1505
F	5945-259-6119	+	RELAY, ARMATURE: Collins part/dwg #970-1716-00			1	1.0	0.5	3.0		K1506
F	5945-283-6604	+	RELAY, ARMATURE: Collins part/dwg #970-1711-00			1	1.0	0.5	3.0		K1508
F	5905-258-6558	+	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF470K			2	1.0	0.5	6.0		R1563 R1564
F	5905-660-6348	+	RESISTOR, FIXED, COMPOSITION: Collins part/dwg #712-4400-00 Item Nos. R1575 thru R1578			4	1.0	0.5	12.0		See desc column
F	5905-279-2643	+	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF101K			6	1.3	0.7	18.0		R811, R812
F	5905-186-2968	+	RESISTOR, FIXED, COMPOSITION: MIL type RC42GF471K Item Nos. R1551 thru R1554			4	1.0	0.5	12.0		See desc column
F	5905-299-2045	+	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF122K Item Nos. R1523.1 thru R1523.10			10	1.7	0.9	30.0		See desc column
F	5905-279-2529	+	RESISTOR, FIXED, COMPOSITION: MIL type RC42GF222J			2	1.0	0.5	6.0		R1517 R1518
F	5905-299-2037	+	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF472K			9	1.7	0.9	27.0		R801, R806 R807
F	5905-299-2029	+	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF103K Item Nos. R1311, R1324 (2 ea)			4	1.0	0.5	12.0		See desc column
F	5905-120-0487	+	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF333K			3	1.0	0.5	9.0		R808 (3 ea)
F	5905-537-6463	+	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF823K			6	1.3	0.7	18.0		R816, R817 (3 ea)
F	5905-171-2006	+	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF104K			6	1.3	0.7	18.0		R803, R804 (3 ea)
F	5905-279-4317	+	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF184K			3	1.0	0.5	9.0		R901, R1550, R1574

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A B C D			AM-738/FRT-22 (continued)								
P	5905-279-1921	+ + +	RESISTOR, FIXED, COMPOSITION: MIL type RC42GF274J			2	1.0	0.5	6.0	R1323 (2 ea)	
P	5905-537-6461	+ + +	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF334K			6	1.3	0.7	18.0	R814, R815 (3 ea)	
P	5905-279-1908	+ + +	RESISTOR, FIXED, COMPOSITION: MIL type RC42GF394J			2	1.0	0.5	6.0	R1301 (2 ea)	
P	5905-299-1993	+ + +	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF474K			1	1.0	0.5	3.0	R1562	
P	5905-192-0390	+ + +	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF105K Item Nos. R1556 thru R1561, R1565			7	1.5	0.8	21.0	See desc column	
P	5905-666-3048	+ + +	RESISTOR, FIXED, COMPOSITION: MIL type RC32GF225K			6	1.3	0.7	18.0	R809, R810 (3 ea)	
P	5905-279-5448	+ + +	RESISTOR, FIXED, WIRE WOUND: Collins part/dwg #747-9044-00			6	1.3	0.7	18.0	R1502 thru R1507	
P	5905-175-5350	+ + +	RESISTOR, FIXED, WIRE WOUND: Collins part/dwg #747-9039-00			2	1.0	0.5	6.0	R1509 R1510	
P	5905-279-9910	+ + +	RESISTOR, FIXED, WIRE WOUND: Collins part/dwg #747-9297-00 Item Nos. R1581.1 thru R1581.10			10	1.7	0.9	30.0	See desc column	
P	5905-270-6517	+ + +	RESISTOR, FIXED, WIRE WOUND: MIL type RW16G121			2	1.0	0.5	6.0	R1511 R1512	
P	5905-296-7756	+ + +	RESISTOR, FIXED, WIRE WOUND: MIL type RB17K90GHOF			1	1.0	0.5	3.0	R1508	
P	5905-283-4739	+ + +	RESISTOR, FIXED, WIRE WOUND: MIL type RW16G312			4	1.0	0.5	12.0	R1513 thru R1516	
P	5905-114-3403	+ + +	RESISTOR, VARIABLE: Collins part/dwg #380-575500			3	1.0	0.5	9.0	R805	
P	5905-644-8928	+ + +	RESISTOR, VARIABLE: Collins part/dwg #377-0023-00			3	1.0	0.5	9.0	R701, R1547, R1548	
P	5905-155-6935	+ + +	RESISTOR, VARIABLE: Collins part/dwg #380-5772-00			3	1.0	0.5	9.0	R813 (3 ea)	

SELWS Form 1 Jan 64 1155 (Supersedes SETMS UN3 TP, which is obsolete)

AM-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER			DESIGNATION BY MODEL			DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
														FIGURE NO.	ITEM NO.
A	B	C	D				AM-738/FRT-22 (continued)								
F				+	+		RESISTOR, VARIABLE: Collins part/dwg #377-0230-00; Item Nos. R1571.1 thru R1571.10; R1572.1 thru R1572.10; R1573.1 thru R1573.10	30		30	3.4	1.0	90.0		See desc column
F				+	+		RETAINER, CAPACITOR: MIL type CPO63A4	2		2	1.0	0.5	4.0		A1532
F				+	+		RETAINER, CAPACITOR: Collins part/dwg #503-9006-002	6		6	1.3	0.7	12.0		E1504, E1599.12
F				+	+		RETAINER, CAPACITOR: Collins part/dwg #503-9222-003	6		6	1.3	0.7	12.0		E1595, E1599.11
F				+	+		RING, RETAINING: Waldes #5133-15	3		3	1.0	0.5	6.0		H736
F				+	+		RING, RETAINER: Waldes #5100-25SMD	2		2	1.0	0.5	4.0		H788
F				+	+		RING, RETAINING: Waldes #5133-12	1		1	1.0	0.5	2.0		H789
F				+	+		RING, RETAINING: Waldes #5101-25	8		8	1.5	0.8	16.0		H1599.234
F				+	+		RING, RETAINING: Waldes #NAS-51-37	10		10	1.7	0.9	20.0		H1599.239
F				+	+		RING, RETAINING: Waldes #5131-25	2		2	1.0	0.5	4.0		H1599.245
F				+	+		RING, RETAINING: Waldes #5100-31	1		1	1.0	0.5	2.0		H1599.276
F				+	+		RING, RETAINING: Waldes #5133-25 SMD	2		2	1.0	0.5	4.0		H1599.296
F				+	+		RING, RETAINING: Waldes #5100-12	48		48	4.5	2.7	96.0		O1560
F				+	+		RING, RETAINING: Waldes #5100-125 SMD	8		8	1.5	0.8	16.0		O1599.59
F				+	+		SEPARATOR, CENTER, LARGE: Collins part/dwg #506-9701-002	8		8	1.5	0.8	16.0		O1515C, O1516C
F				+	+		SEPARATOR, CENTER, SMALL: Collins part/dwg #506-9701-002	8		8	1.5	0.8	16.0		O1515D, O1516D
F				+	+		SEPARATOR, LARGE: Collins part/dwg #506-9708-003	24		24	2.6	1.4	48.0		O1515A, O1516A
F				+	+		SEPARATOR, SMALL: Collins part/dwg #506-9707-003	24		24	2.6	1.4	48.0		O1515B, O1516B
F				+	+		SHAFT, COIL, SPLINED: Collins part/dwg #504-1622-001	2		2	1.0	0.5	2.0		O1599.40

SELMS Form 1 Jun 64

1155

(Supersedes SELMS 003 TF, which is obsolete)

AM-738/FRT-22



SOURCE CODE	DESIGNATION BY MODEL				FEDERAL STOCK NUMBER	DESCRIPTION	UNIT OF ISSUE	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
	A	B	C	D								FIGURE NO.	ITEM NO.
						AM-738/FRT-22 (continued)							
	O				5960-564-4755	SHIELD, ELECTRON TUBE: Collins part/dwg #541-6554-003		6	1.3	0.7	60.0		
	O				5960-546-7191	SHIELD, ELECTRON TUBE: Collins part/dwg #541-6550-003		1	1.0	0.5	10.0	E1574	
	F				5935-222-9828	SOCKET, ELECTRON TUBE: MIL type TS103C01 Item Nos. XV801, XV802 (3ea)		6	1.3	0.7	18.0	See desc column	
	F				5935-222-9741	SOCKET, ELECTRON TUBE: Eby #8326 Item Nos. XV1301, XV1303 (2 ea)		4	1.0	0.5	12.0	See desc column	
	F				5935-260-0516	SOCKET, ELECTRON TUBE: MIL type TS103P01		1	1.0	0.5	3.0	XV1507	
	F				5820-631-6882	SPRING BACKUP: Collins part/dwg #543-0295-002		12	1.9	1.0	24.0	01545	
	F				5820-547-9153	SPRING, HELICAL, EXTENSION: Collins part/dwg #505-7510-00 Item Nos. 0716, 01577, 01578		3	1.0	0.5	15.0	See desc column	
	F				5820-547-9148	SPROCKET, WHEEL: Collins part/dwg #504-1827-002		1	1.0	0.5	2.0	01505	
	F				5820-326-3607	SPROCKET, WHEEL: Collins part/dwg #504-1833-003		1	1.0	0.5	2.0	01506	
	F				5820-547-9126	SPROCKET, WHEEL: Collins part/dwg #504-1826-002		1	1.0	0.5	2.0	01507	
	F				5820-547-9127	SPROCKET, WHEEL: Collins part/dwg #504-1868-001		1	1.0	0.5	2.0	01508	
	F				5820-392-6425	SPROCKET, CHAIN: Collins part/dwg #504-9098-002		1	1.0	0.5	2.0	01550	
	F				5820-974-9803	SPROCKET, CHAIN: Collins part/dwg #504-1921-002		1	1.0	0.5	2.0	01552	
	F				5820-326-3606	SPROCKET, WHEEL: Collins part/dwg #504-1832-003		1	1.0	0.5	2.0	01509	
	F				5820-547-9150	SPROCKET, WHEEL: Collins part/dwg #504-1707-002		1	1.0	0.5	2.0	01538	

SELMS Form 1155 (Successes SELMS 003 TFR, which is obsolete)  
1 Jun 64

AM-738/FRT-22

Army-PF Memorandum, NJ-MON 1509-4-4

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
	5820-547-9151	+	+	AM-738/PRT-22 (continued)		1	1.0	0.5	2.0		01539
P				SPROCKET, WHEEL: Collins part/dwg #							
	5820-547-9129	+	+	SPROCKET, WHEEL: Collins part/dwg		1	1.0	0.5	2.0		01540
P				#504-1708-002							
	5820-547-9152	+	+	SPROCKET, WHEEL: Collins part/dwg		1	1.0	0.5	2.0		01541
P				#504-1799-003							
	5820-547-9130	+	+	SPROCKET, WHEEL: Collins part/dwg		1	1.0	0.5	2.0		
P				#504-1800-003							
	5820-547-9131	+	+	SPROCKET, WHEEL: Collins part/dwg		1	1.0	0.5	2.0		01543
P				#504-1701-002							
	5915-503-2250	+	+	SUPPRESSOR, PARASITIC: Collins		2	1.0	0.5	10.0		E1547
P				part/dwg #504-2114-001							E1548
	5930-636-4397	+	+	SWITCH, KNIFE: Collins part/dwg		1	1.0	0.5	3.0		S1520
P				#504-4522-002							
	5930-476-1206	+	+	SWITCH, PLATE: Collins part/dwg		1	1.0	0.5	3.0		P/O
P				#506-7642-002							S1520
	5920-296-3916	+	+	SWITCH, LEVER: Collins part/dwg		1	1.0	0.5	3.0		S1503
P				#503-8397-002							
	5930-537-7365	+	+	SWITCH, PRESSURE: Collins part/dwg		1	1.0	0.5	5.0		S1507
P				#260-1299-00 (NOTE: used w/serial							
				#17 and UP05 Order 3456-PH-5.2 and							
				all other orders)							
	5930-301-5079	+	+	SWITCH, PUSH: CH Bulletin 10250H		1	1.0	0.5	5.0		S1508
P											
	5930-296-6513	+	+	SWITCH, PUSH: C-H Bulletin 10250H		1	1.0	0.5	5.0		S1509
P											
	5930-309-5548	+	+	SWITCH, PUSH: Collins part/dwg		1	1.0	0.5	5.0		S1515,
P				#504-1792-003							A,B,C
	5930-224-5569	+	+	SWITCH, PUSH-PULL: GE #7460330-g4		3	1.0	0.5	15.0		See desc
P				Item Nos. S1510A,B,S-1511A,B,							column
				S1512A,B							
	5930-296-6337	+	+	SWITCH, ROTARY: Collins part/dwg		1	1.0	0.5	5.0		S1501
P				#259-0157-00							
	5930-548-6338	+	+	SWITCH, ROTARY: Collins part/dwg		1	1.0	0.5	5.0		S1502
P				#259-0059-00							

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A B C D			AM-738/PRT-22 (continued) - SWITCH, ROTARY: Collins part/dwg #259-1046-00 Item Nos. S1525.1 thru S1525.10			10	1.7	0.9	50.0		See desc column
F	5930-548-6869	+	SWITCH, SENSITIVE: Collins part/dwg #260-0700-00 (NOTE: use w/serial No. 1 thru 16 only of Order 3455-PH-52)			1	1.0	0.5	5.0		S1507
F	5930-549-0598	+	SWITCH, SENSITIVE: GE #CR1070C123-I4 Item Nos. S701, S702, S1516 thru S1519			6	1.3	0.7	30.0		See desc column
F	5930-636-2606	+	SWITCH, SECTION, ROTARY: Collins part/dwg #269-1611-00			1	1.0	0.5	3.0		
F	5930-697-3380	+	SWITCH SECTION, ROTARY: Collins part/dwg #269-1640-00			1	1.0	0.5	3.0		S1524
F	5930-642-9026	+	SWITCH SECTION, ROTARY: Collins part/dwg #269-1636-00			3	1.0	0.5	9.0		S712A, S712N, S1523
F	5930-636-2600	+	SWITCH SECTION, ROTARY: Collins part/dwg #269-1639-00 Item Nos. S712B thru S712J, S712K, S712M			10	1.7	0.9	30.0		See desc column
F	5930-188-7250	+	SWITCH, TOGGLE: MIL type ST42D; Item Nos. S1526.1 thru S1526.10			10	1.7	0.9	50.0		See desc column
F	5930-274-5116	+	SWITCH, TOGGLE: Trumbull #22285			1	1.0	0.5	5.0		S1506
F	5820-547-9155	+	SWIVEL, GIMBAL: Collins part/dwg #504-1760-002			1	1.0	0.5	2.0		01524
F	5940-201-7449	+	TERMINAL BOARD; Jones HB #141-6; Collins part/dwg #367-4060-00			2	1.0	0.5	6.0		E801, E802
P	5940-171-0580	+	TERMINAL BOARD; Jones HP #12-142; Collins part/dwg #367-5120-00 Item Nos. E1501 thru E1506, E1510			7	1.5	0.8	21.0		See desc column
F	5940-192-9990	+	TERMINAL BOARD; Jones HB #6-142; Collins part/dwg #367-5060-00 Item Nos. E1507, E1508, E1509, E1511, E1572			5	1.3	0.7	15.0		See desc column

SEIAMS Pam  
1 Jun 64

1155 - Supplemental RELIANCE  
AM-738/PRT-22

1155 - Supplemental RELIANCE  
AM-738/PRT-22

Amey-F. H. Moush, NJARON 1956-44

SOURCE CODE	FEDERAL STOCK NUMBER			DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
												FIGURE NO.	ITEM NO.
A   B   C   D					AM-738/FRT-22 (continued)								
P	5940-193-0217	+	+		TERMINAL BOARD: Jones HB #4-142; Collins part/dwg #367-5040-00			2	1.0	0.5	6.0	E1514, E1515	
P	5940-179-1304	+	+		TERMINAL BOARD: Jones HB #8-142; Collins part/dwg #367-5080-00			1	1.0	0.5	3.0		
P	5940-272-5040	+	+		TERMINAL BOARD: Jones HB #2-141Y; Collins part/dwg #367-0100-00			1	1.0	0.5	3.0	E1575	
P	5305-561-0979	+	+		THUMSCREW: Collins part/dwg #505-8504-002			2	1.0	0.5	10.0	H734	
P	5950-648-5714	+	+		TRANSFORMER, AUDIO FREQUENCY: Thondarson #T-51320A			3	1.0	0.5	9.0	T801 (3 ea)	
P	5950-646-2432	+	+		TRANSFORMER, POWER, STEP-DOWN: Chic Transf #12875; Collins part/dwg #672-0257-00			1	1.0	0.5	3.0	T902	
P	5950-246-5269	+	+		TRANSFORMER, POWER, STEP-DOWN: GE #90G777			2	1.0	0.5	6.0	TI501, TI502	
P	5950-246-5274	+	+		TRANSFORMER, POWER, STEP-DOWN: Collins part/dwg #672-1610-00			1	1.0	0.5	3.0	TI503	
P	5950-648-1863	+	+		TRANSFORMER, POWER, STEP-DOWN: Chic Transf #17807; Collins part/dwg #662-0106-00			1	1.0	0.5	3.0	TI505	
P	5950-569-0105	+	+		TRANSFORMER, POWER, STEP-DOWN: Collins part/dwg #672-0467-00			1	1.0	0.5	3.0	T901	
P	5960-318-7167	+	+		TUBING: Collins part/dwg #192-1013-00			2	1.0	0.5	4.0	XV1501A XV1504A	
P	5310-514-6867	+	+		WASHER, KEY: Collins part/dwg #503-0643-00			32	3.4	1.9	160.0	H701, H1501	
P	5310-550-4107	+	+		WASHER, LOCK: Shakeup #1832-00; Collins part/dwg #373-0077-00			3	1.0	0.5	15.0	H1599.185	
P	5330-291-8935	+	+		WASHER, NON-METALLIC: Collins part/dwg #302-0038-00			9	1.9	1.0	45.0	H1599.11	
P	5330-527-9299	+	+		WASHER, NON-METALLIC: Collins part/dwg #504-1615-00			6	1.3	0.7	30.0	H1599.18	

SEELE Form  
1 Jan 64

1155 (Supersedes BELMO 003 TF, which is obsolete)

AM-738/FRT-22



SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A B C D											
F	5330-527-9300	+	AM-738/FRT-22 (continued) WASHER, NONMETALLIC: Collins part/dwg #504-1616-00 CONTROL, POWER SUPPLY C-2446/FRT-22A GROUP			6	1.3	0.7	30.0		H1599.189
F	5977-284-9263		BRUSH, ELECTRICAL CONTACT: Collins part/dwg #260-0788-00 (Set of two)			1	1.0	0.5	10.0		K1701C
F	5925-644-9732		CIRCUIT BREAKER: Collins part/dwg #260-2559-00			1	1.0	0.5	5.0		K1701
F	5950-568-4858		COIL, CIRCUIT BREAKER: Collins part/dwg #260-0790-00			1	1.0	0.5	3.0		K1701A
F	5925-523-1815		CONTACT ASSEMBLY, ELECTRICALLY: Collins part/dwg #260-0796-00			1	1.0	0.5	2.0		K1701I
F	5925-284-3591		CONTACT, ELECTRICAL: Collins part/dwg #260-0797-00			1	1.0	0.5	3.0		K1701J
F	5925-354-4596		CONTACT, ELECTRICAL: Collins part/dwg #260-0798-00			1	1.0	0.5	3.0		K1701K
O	5920-636-0961		FUSE, CARTRIDGE: Collins part/dwg #264-0055-00			2	1.0	0.5	100.0		K1701, K1702
F	5920-280-5079		FUSEHOLDER: Collins part/dwg #265-5020-00			2	1.0	0.5	6.0		XF1701, XF1902
F	5925-196-0391		LEVER: Collins part/dwg #260-0793-00			1	1.0	0.5	4.0		K1701D
F	6105-692-6390		MOTOR, ALTERNATING AND DIRECT CURRENT: Collins part/dwg #260-0787-00			1	1.0	0.5	2.0		K1701B
F	5905-532-7960		RESISTOR, FIXED, WIRE WOUND: Collins part/dwg #260-0795-00			1	1.0	0.5	3.0		K1701H
F	5930-340-3588		SWITCH, ROTARY: Collins part/dwg #260-0792-00			1	1.0	0.5	5.0		K1701F
F	5940-498-1852		TERMINAL BOARD: Collins part/dwg #367-5160-00			1	1.0	0.5	3.0		E1701
F	5925-523-1858		TRIPPER, CIRCUIT BREAKER: Collins part/dwg #260-0800-00			1	1.0	0.5	3.0		K1701L

SELMAS Form 1155 (Supersedes SELMAG 003 TFE, which is obsolete)  
1 Jun 64

AM-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
									FIGURE NO.	ITEM NO.
A B C D			AM-738/FRT-22 (continued) POWER CONTROL C-598/FRT-6 GROUP							
F	5977-284-9263		BRUSH, ELECTRICAL CONTACT: Collins part/dwg #260-0788-00 (Set of two)		1	1.0	0.5	10.0	K1701C	
F	5925-644-9732		CIRCUIT BREAKER: Wemco #1310-876; Collins part/dwg #260-0789-00		1	1.0	0.5	5.0	K1701	
F	5950-568-4858		COIL, CIRCUIT BREAKER: Wemco #1019680 Collins part/dwg #260-0790-00		1	1.0	0.5	5.0	K1701A	
F	5925-354-4596		CONTACT, ELECTRICAL: Wemco #1346141		1	1.0	0.5	3.0	K1701K	
F	5925-284-3591		CONTACT, ELECTRICAL: Wemco #1318655		1	1.0	0.5	3.0	K1701J	
F	5925-523-1815		CONTACT ASSEMBLY, ELECTRICAL: Wemco #1310970		1	1.0	0.5	2.0	K1701	
O	5920-636-0961		FUSE, CARTRIDGE: Bussman #10-25010; Collins part/dwg #264-0055-00		2	1.0	0.5	100.0	F1701, F1702	
F	5920-280-5079		FUSEHOLDER: Collins part/dwg #655-0200-0		1	1.0	0.5	3.0	XF1701, XF1702	
F	5925-196-0391		LEVER: Wemco #1318833; Collins part/dwg #260-0793-00		1	1.0	0.5	4.0	K1701D	
F	6105-692-6390		MOTOR, ALTERNATING AND DIRECT CURRENT: Wemco #1170432; Collins part/dwg #260-0787-00		1	1.0	0.5	2.0	K1701B	
F	5905-532-7960		RESISTOR, FIXED, WIRE WOUND: WL #160F		1	1.0	0.5	3.0	K1701H	
F	5930-340-3588		SWITCH, ROTARY: Wemco #1081150		1	1.0	0.5	5.0	K1701F	
F	5940-198-1852		TERMINAL BOARD: Jones HB #16-142		1	1.0	0.5	3.0	E1701	
F	5925-523-1858		TRIPPER, CIRCUIT BREAKER: Wemco #1332275		1	1.0	0.5	5.0	K1701L	
			POWER SUPPLY PP-1089/FRT-22 GROUP							
F	5820-399-7672		BAR, ASSEMBLY, SHORTING: Collins part/dwg #506-9959-002		1	1.0	0.5	5.0	E1615	

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
			AM-738/FRT-22 (continued)								
	4114-255-005		FLOWER: Collins part/dwg #009-1112-00			1	1.0	0.5	5.0		B1601
	5925-283-4842		CABLE ASSEMBLY, POWER ELECTRICAL: Collins part/dwg #503-8530-004			1	1.0	0.5	5.0		W1601
	6145-846-7697		CABLE, HIGH VOLTAGE: 15,000 volt high-tension high-temperature cable				R	R			
	5920-244-5150		CAP, ELECTRICAL: Bussman #HXP-JQRZ Item Nos. XF1601A THRU XF1607A			7	2.1	1.1	21.0		See desc column
	5910-191-2734		CAPACITOR, FIXED, MICA DIELECTRIC: MIL type CM50B47M; Item Nos. C1605, C1606, C1607			3	1.0	0.5	9.0		See desc column
	5910-184-2697		CAPACITOR, FIXED, MICA DIELECTRIC: MIL type CM35B472M			1	1.0	0.5	3.0		C1611
	5910-267-5044		CAPACITOR, FIXED, PAPER DIELECTRIC: Collins part/dwg #930-0331-00 Item No. C1601, C1602, C1608, C1609, C1610			5	1.0	0.5	15.0		See desc column
	5910-161-6415		CAPACITOR, FIXED, PAPER DIELECTRIC: MIL type CP70E1FG156K			2	1.0	0.5	6.0		C1603, C1604
	5925-040-7815		CIRCUIT BREAKER: GE #12PJC11AA2 Item Nos. K1601 thru K1606			6	1.3	0.7	18.0		See desc column
	5945-259-2171		CIRCUIT BREAKER: GE #12PJC11A4TF			1	1.0	0.5	3.0		K1607
	5925-319-0742		CIRCUIT BREAKER: Heinenmann Code # 74193			1	1.0	0.5	3.0		SL1601
	5925-270-5957		CIRCUIT BREAKER: Heinenmann #2263S			1	1.0	0.5	3.0		SL1602
	5925-270-5959		CIRCUIT BREAKER: Collins part/dwg #260-0244-00			1	1.0	0.5	3.0		SL1603
	5925-279-5581		CIRCUIT BREAKER: Collins part/dwg #260-0404-00			1	1.0	0.5	3.0		SL1604
	5925-259-7783		CIRCUIT BREAKER: Collins part/dwg #260-0367-00			1	1.0	0.5			SL1605
	5925-283-7979		CIRCUIT BREAKER: Collins part/dwg #260-0234-00			1	1.0	0.5	3.0		SL1607

SOURCE CODE	FEDERAL STOCK NUMBER				DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
	A	B	C	D									FIGURE NO.	ITEM NO.
						AM-738/FRT-22 (continued)			1	1.0	0.5	3.0		K1608
						CIRCUIT BREAKER: Collins part/dwg #405-0103-00								
						CLIP, ELECTRICAL: Collins part/dwg #301-1005-00			16	2.6	1.4	48.0		E1617
						CLIP, ELECTRICAL: Multi Elect #2026-S			56	4.5	2.7	168.0		E1628
						CLIP, ELECTRICAL: Multi Elect #2022J			2	1.0	0.5	6.0		E1629
						CLIP, ELECTRICAL: Multi Elec #2020J			18	2.5	1.3	54.0		
						COIL RELAY: AB #0A07-B Item Nos. K1611F, K1619D, K1616D, K1617D, K1621C			5	1.3	0.7	15.0		See desc column
						COIL, RELAY: AB #1A06-B			2	1.0	0.5	6.0		K1612C, K1613C
						CONNECTOR, PLUG, ELECTRICAL: Collins part/dwg #370-2023-00			1	1.0	0.5	3.0		P1601
						CONNECTOR, PLUG, ELECTRICAL: Cannon Elect #R1K-30-24C-1-1/8			1	1.0	0.5	3.0		P1602
						CONNECTOR, RECEPTACLE, ELECTRICAL: Cannon Elect #R1K-30-31SL			1	1.0	0.5	3.0		J1601
						CONNECTOR, RECEPTACLE, ELECTRICAL: Cannon Elect #1K-30-32S			1	1.0	0.5	3.0		J1602
						CONTACT, ELECTRICAL: GE #6174439G1 Item Nos. K1601A thru K1608A			16	2.3	1.2	48.0		See desc column
						CONTACT, ELECTRICAL: GE #6174440G-1 Item Nos. K1601B thru K1608B			16	2.3	1.2	48.0		See desc column
						CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0022-00			1	1.0	0.5	2.0		K1611A
						CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0023-00			1	1.0	0.5	2.0		K1611B
						CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0032-00 Item Nos. K1611C-(6 ea), K1617A, K1619A			3	1.0	0.5	6.0		See desc column

SEL-15 Form  
1 Jun 64

1155 (Revised RELAMP 003 TP, which is obsolete)

AM-738/FRT-22



SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A B C D			AM-738/FRT-22 (continued)								
F	5945-259-6471		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0033-00 Item Nos. K1611D, K1617B, K1619B			3	1.0	0.5	6.0		See desc column
F	5945-234-5796		CONTACT, ELECTRICAL: Collins part/dwg #406-1102-00 Item Nos. K1611E, K1616C-(2 ea), K1617C-(3 ea), K1619C-(3 ea)			19	2.3	1.2	57.0		See desc column
F	5945-224-5782		CONTACT, ELECTRICAL: Collins part/dwg #406-1100-00 Item Nos. K1621A-(6 ea) K1613A-(8 ea)			14	2.1	1.1	42.0		See desc column
F	5945-283-6533		CONTACT, ELECTRICAL: Collins part/dwg, #406-1900-00 Item Nos. K1612B (3 ea), K1613B (4 ea)			7	1.3	0.7	21.0		See desc column
F	5945-259-6476		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0034-00			1	1.0	0.5	2.0		K1616A
F	5945-259-6474		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0035-00			1	1.0	0.5	2.0		K1617B
F	5945-259-6475		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0024-00			1	1.0	0.5	2.0		K1621A
F	5945-259-6472		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0025-00			1	1.0	0.5	2.0		K1621B
O	5960-108-0252		ELECTRON TUBE: MIL type 3B28 Item Nos. V1613 thru V1616			4	35.2	17.6	400.0		See desc column
O	5960-188-0944		ELECTRON TUBE: MIL type 4B32 (OR) Item Nos. V1601 thru V1612			12	105.6	52.8	1200.0		See desc column
O	5910-188-8630		ELECTRON TUBE: MIL type 575A (OR item) Item Nos. V1601 thru V1612			12	105.6	52.8	1200.0		See desc column
F	4130-618-3285		FILTER, AIR CONDITIONING: Air Maze #00736			2	1.0	0.5	6.0		01601
O	5920-284-9220		FUSE, CARTRIDGE: MIL type RC2G1ROOB Item Nos. F1601 thru F1607			7	2.1	1.1	350.0		See desc column
F	5920-570-5117		FUSEHOLDER: Busman HRP-9-LR Item Nos. XF1601 thru XF1607			7	1.0	0.5	21.0		See desc column
F	5970-144-1559		INSULATOR, BOWL: MIL type NS4W4601			24	1.0	0.5	48.0		E1616

SEIUS Form  
1 Jun 64

1155 (Supersedes BELMB 003 TP, which is obsolete)

AM-738/FRT-22

30

Amv-Ft. Monmouth, NJ-LMDN 1830644

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
F	5970-284-8427		AM-738/FRT-22 (continued) INSULATOR, STANDOFF: MIL type NS4W0308			32	1.0	0.5	64.0		E1624
F	5970-117-5322		INSULATOR, STANDOFF: Collins part/dwg #503-8427-002			4	1.0	0.5	8.0		E1611
F	5970-117-5181		INSULATOR, STANDOFF: MIL type NS4W0312			48	1.0	0.5	96.0		E1618
F	5970-284-8166		INSULATOR, STANDOFF: MIL type NS4W0316			26	1.0	0.5	52.0		E1619
F	5970-284-8656		INSULATOR, STANDOFF: Collins part/dwg #190-1175-00			30	1.0	0.5	60.0		E1623
F	5970-284-4632		INSULATOR, STANDOFF: Collins part/dwg #190-1172-00			8	1.0	0.5	16.0		E1625
F	5970-151-8022		INSULATOR, STANDOFF: MIL type NS4W0324			8	1.0	0.5	16.0		E1626
F	5970-117-5325		INSULATOR, STANDOFF: Collins part/dwg #190-1176-00			6	1.0	0.5	12.0		E1627
F	5970-117-5189		INSULATOR, STANDOFF: Centralab #2X783			2	1.0	0.5	4.0		E1642
O	5355-667-9095		KNOB: Collins part/dwg #504-4617-002			2	1.0	0.5	6.0		E1633, E1634
O	5355-667-9236		KNOB: Collins part/dwg #502-9138-002			1	1.0	0.5	3.0		E1636
O	5355-667-9388		KNOB: Collins part/dwg #503-8168-003			1	1.0	0.5	3.0		E1635
F	6240-313-8980		LAMP, GLOW: Drake Mfg #201001 Item Nos. 11610 thru 11616			7	2.1	1.1	350.0		See desc column
O	6240-143-3060		LAMP, INCANDESCENT: Collins part/dwg #262-0041-00 Item Nos. 11601 thru 11609			9	2.5	1.3	450.0		See desc column
F	6250-270-4260		LAMPHOLDER: Dialco #9-S-4634-L-46; Collins part/dwg #262-0042-00 Item Nos. 111601 thru 111603			3	1.0	0.5	15.0		See desc column
F	6210-299-3908		LENS, INDICATOR LIGHT: Collins part/ dwg #262-0106-00			2	1.0	0.5	10.0		X11604A, X11607A

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A 181 C D			AM-738/FRT-22 (continued)								
F	6210-299-3880		LENS, INDICATOR LIGHT: Collins part/dwg #262-0105-00			2	1.0	0.5	10.0		X11605A, X11609A
F	6210-299-3882		LENS, INDICATOR LIGHT: Collins part/dwg #262-0104-00			2	1.0	0.5	10.0		X1606A, X1608A
F	6210-299-6381		LIGHT, INDICATOR: Dialco #51702-67 Item Nos. X1604 thru X1609			6	1.0	0.5	30.0		See desc column
F	6625-663-8107		METER, TIME, ELECTRIC: Weston #691			2	1.0	0.5	10.0		M1604, M1605
F	5950-519-6041		REACTOR: Thordarson #T51355			1	1.0	0.5	2.0		L1602
F	5950-295-7813		REACTOR: Collins part/dwg #678-0365-00			1	1.0	0.5	2.0		L1601
F	5945-681-9941		RELAY, SOLENOID: A.B. #B700			1	1.0	0.5	5.0		K1611
F	5945-502-9057		RELAY, SOLENOID: A.B. #Bal 702 size 1			1	1.0	0.5	5.0		K1612
F	5945-258-4065		RELAY, SOLENOID: Collins part/dwg #405-0363-00			1	1.0	0.5	5.0		K1613
F	5945-665-7148		RELAY, SOLENOID: A.B. #B-200, Bal 700			1	1.0	0.5	5.0		K1616
F	5945-232-7708		RELAY, SOLENOID: A.B. #B-300, Bal 700			2	1.0	0.5	10.0		K1617 K1619
F	5945-259-6445		RELAY, SOLENOID: Collins part/dwg #405-0045-00			1	1.0	0.5	5.0		K1621
F	5945-259-6604		RELAY, MOTOR-DRIVEN: Collins part/dwg #402-0054-00			1	1.0	0.5	5.0		K1614
F	5945-813-0609		RELAY, MOTOR-DRIVEN: Collins part/dwg #402-0029-00			1	1.0	0.5	5.0		K1615
F	5905-186-2968		RESISTOR, FIXED, COMPOSITION: MIL type RC420F471K			2	1.0	0.5	6.0		R1668 R1669
F	5905-279-4317		RESISTOR, FIXED, COMPOSITION: MIL type RC32GF184K			7	1.0	0.5	21.0		R1658 thru R1664
F	5905-101-0743		RESISTOR, FIXED, WIRE WOUND: MIL type NFA 405			2	1.0	0.5	6.0		R1601, R1602
F	5905-306-2190		RESISTOR, FIXED, WIRE WOUND: GE #CR9033B1C23			12	1.3	0.7	36.0		R1646 thru R1657

SELMS Form  
1 Jun 64

1155 (Supersedes SELMS 003 TF, which is obsolete)

AM-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
P	5905-309-5515		AM-738/FRT-22 (continued) RESISTOR, FIXED, WIRE WOUND: GE #09033B5C45			4	1.0	0.5	12.0		R1620 thru R1623 R1628 thru R1637
P	5905-542-8273		RESISTOR, FIXED, WIRE WOUND: MIL type RW1083107			10	1.3	0.7	30.0		
P	5905-542-8218		RESISTOR, FIXED, WIRE WOUND: MIL type RW168500			4	1.0	0.5	12.0		R1624 thru R1627
P	5905-542-8208		RESISTOR, FIXED, WIRE WOUND: MIL type RW108800			6	1.0	0.5	18.0		R1614 thru R1619
P	5905-247-6662		RESISTOR, FIXED, WIRE WOUND: MIL type RW166312			5	1.0	0.5	15.0		R1641 thru R1645
P	5905-542-8206		RESISTOR, FIXED, WIRE WOUND: MIL type RW108402			10	1.3	0.7	30.0		R1604 thru R1613
P	5905-231-9826		RESISTOR, VARIABLE: Collins part/dwg #749-7677-00			2	1.0	0.5	6.0		R1639, R1640
P	5905-636-6299		RESISTOR, VARIABLE: MIL type RF401F500K			1	1.0	0.5	3.0		R1638
P	5905-636-6696		RESISTOR, FIXED, WIRE WOUND: MIL type RW146163			1	1.0	0.5	3.0		R1603
P	5340-531-6811		RING, RETAINING: Collins part #340-0013-00			10	1.0	0.5	20.0		R1627
P	5935-229-5670		SOCKET, ELECTRON TUBE: B.F. Johnson #123-211-22 Item Nos. XV1601 thru XV1612			12	1.3	0.7	36.0		See desc column
P	5935-129-3070		SOCKET, ELECTRON TUBE: BF Johnson #123-209-51			4	1.0	0.5	12.0		XV1613 thru XV1616
P	5930-224-5569		SWITCH, PUSH-PULL: GE 746-0330-d4 Item Nos. S1611, S1612, S1613			3	1.0	0.5	15.0		See desc column
P	5930-296-3916		SWITCH, LEVER: Collins part #503-8397-002			1	1.0	0.5	5.0		S1620

SELMIS Form  
1 Jan 64  
1155 (Supersedes SELMIS 003 TF, which is obsolete)

Army-Ft. Monmouth, NJ-MON 1550-64



SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A B C D			AM-738/FRT-22 (continued)								
P	5930-201-5079		SWITCH, PUSH: C-1-1 Bulletin 10250H			1	1.0	0.5	5.0		SI609
P	5930-296-6513		SWITCH, PUSH: Collins part #260-0352-00			1	1.0	0.5	5.0		SI610
P	5930-549-0533		SWITCH, ROTARY: Collins part #260-0855-00			1	1.0	0.5	5.0		SI608
P	5930-548-6453		SWITCH, ROTARY: Collins part #259-0314-00			1	1.0	0.5	5.0		SI621
P	5930-548-6133		SWITCH, ROTARY: Collins part #260-0354-00			1	1.0	0.5	5.0		SI622
P	5930-274-5116		SWITCH, TOGGLE: Collins part #260-0803-00			1	1.0	0.5	5.0		SI606
P	5940-271-2257		TERMINAL BOARD: Jones HB #12-142 Item Nos. EI602 thru EI607, EI609, EI610			8	1.3	0.7	24.0		See desc column
P	5940-193-0217		TERMINAL BOARD: Jones HB 4-142			2	1.0	0.5	6.0		EI608 EI613
P	5950-251-7775		TRANSFORMER, POWER, STEP-DOWN: Collins part# 672-0152-00			6	1.0	0.5	18.0		TI601 thru TI606
P	5950-295-7250		TRANSFORMER, POWER, STEP-DOWN: Chd Trans #13094			1	1.0	0.5	3.0		TI607
P	5950-254-0037		TRANSFORMER, POWER, STEP-UP: Thordarson #T51354			1	1.0	0.5	3.0		TI608
P	6625-649-2816		VOLTMETER: Weston #741-0 to 8.0		NX	1	1.0	0.5 d	4.0		MI601
P	6625-668-9312		VOLTMETER: Weston #744, 0-10 VAC		NX	1	1.0	0.5	4.0		MI603
P	6625-668-9316		VOLTMETER: Weston #744, 0-300 VAC POWER SUPPLY PP-1970/FRT-22A GROUP		NX	1	1.0	0.5	4.0		MI602
P	6130-399-7672		BAR ASSEMBLY, SHORTING: Collins part/dwg #506-9959-002			1	1.0	0.5	5.0		EI615
P	4140-255-9057		BLOWER: Collins part/dwg #009-1172-00			1	1.0	0.5	5.0		EI601

SELAS Form  
1 Jun 64

Ampt-Pt. Monmouth, NJ-JAN 1950-54

1155 (Supersedes BELAS 013 TP, which is obsolete)  
AM-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
									FIGURE NO.	ITEM NO.
A   B   C   D			AM-738/FRT-22 (continued)							
F	5995-383-3802		CABLE ASSEMBLY, POWER ELECTRICAL: Collins part/dwg #503-8530-004		1	1.0	0.5	5.0		
O	5920-244-5150		CAP, ELECTRICAL: Bussman #HKP-JQFZ Item Nos. XF1601A thru XF1607A		7	2.1	1.1	21.0		See desc column
F	5910-191-2734		CAPACITOR, FIXED, MICA DIELECTRIC: MIL type CM50B472M; Item Nos. C1605, C1606, C1607		3	1.0	0.5	9.0		See desc column
F	5910-184-2697		CAPACITOR, FIXED, MICA DIELECTRIC: MIL type CM35B472M		1	1.0	0.5	3.0		C1611
F	5910-667-5044		CAPACITOR, FIXED, PAPER DIELECTRIC: Collins part/dwg #930-0331-00 Item Nos. C1601, C1602, C1608, C1609, C1610		5	1.0	0.5	15.0		See desc column
F	5910-161-6415		CAPACITOR, FIXED, PAPER DIELECTRIC: MIL type CP70E1FG156K		2	1.0	0.5	6.0		C1603, C1604
F	5925-049-7815		CIRCUIT BREAKER: GE #12PJCL1A2 Item Nos. K1601 thru K1606		6	1.3	0.7	18.0		See desc column
F	5945-259-2171		CIRCUIT BREAKER: GE #12PJCL1A4TF		1	1.0	0.5	3.0		K1607
F	5925-319-0742		CIRCUIT BREAKER: Heinemann #74193		1	1.0	0.5	3.0		S1601
F	5920-270-5957		CIRCUIT BREAKER: Heinemann #2263S		1	1.0	0.5	3.0		S1602
F	5925-270-5959		CIRCUIT BREAKER: Collins part #260-0244-00		1	1.0	0.5	3.0		S1603
F	5925-279-5581		CIRCUIT BREAKER: Collins part/dwg #260-0404-00		1	1.0	0.5	3.0		S1604
F	5925-259-7783		CIRCUIT BREAKER: Collins part/dwg #260-0867-00		1	1.0	0.5	3.0		S1605
F	5935-283-7979		CIRCUIT BREAKER: Collins part/dwg #260-0234-00		1	1.0	0.5	3.0		S1607
F	5925-319-0739		CIRCUIT BREAKER: Collins part/dwg #405-0103-00		1	1.0 q	0.5	3.0		K1608
F	5940-501-8726		CLIP, ELECTRICAL: Collins part/dwg #301-1005-00		16	2.6	1.4	48.0		E1617

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
									FIGURE NO.	ITEM NO.
A B C D			AM-738/FRT-22 (continued)							
P	5920-309-5185		CLIP, ELECTRICAL: Multi Elect #2026-S		56	4.5	2.7	168.0	E1628	
P	5940-279-1297		CLIP, ELECTRICAL: Multi Elect #2022J		2	1.0	0.5	6.0	E1629	
P	5940-204-5233		CLIP, ELECTRICAL: Multi Elect #2020J		18	2.5	1.3	54.0		
P	5950-545-7860		COIL, RELAY: A B #0A07-B; Item Nos. K1611F, K1619D, K1616D, K1617D, K1621C		5	1.3	0.7	15.0	See desc column	
P	5950-510-4666		COIL, RELAY: A.B. #1A06-B		2	1.0	0.5	6.0	K1621C K1613C	
P	5935-201-8470		CONNECTOR, PLUG: Collins part/dwg #370-2023-00		1	1.0	0.5	3.0	P1601	
P	5935-201-8472		CONNECTOR, PLUG: Cannon Elect #RLK-30-24C-1-1/8		1	1.0	0.5	3.0	P1602	
P	5935-257-7195		CONNECTOR, RECEPTACLE: Cannon Elect #RLK-30-31SL		1	1.0	0.5	3.0	J1601	
P	5935-283-3746		CONNECTOR, RECEPTACLE: Cannon Elect #IK-30-32S		1	1.0	0.5	3.0	J1602	
P	5945-392-5647		CONTACT, ELECTRICAL: GE #6174439G1 Item Nos. K1601A thru K1608A		16	2.3	1.2	48.0	See desc column	
P	5945-392-5648		CONTACT, ELECTRICAL: GE #6174440G-1 Item Nos. K1601B thru K1608B		16	2.3	1.2	48.0	See desc column	
P	5945-224-5781		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0023-00		1	1.0	0.5	3.0	K1611B	
P	5945-259-6473		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0032-00 Item Nos. K1611C (6 ea), K1617A, K1619A		3	1.0	0.5	9.0	See desc column	
P	5945-259-6471		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0033-00 Item Nos. K1611D, K1617B, K1619B		3	1.0	0.5	9.0	See desc column	
P	5945-234-5796		CONTACT, ELECTRICAL: Collins part/dwg #406-1102-00 Item Nos. K1611E, K1616C (2 ea), K1617C (3 ea), K1619C (3 ea)		19	2.3	1.7	57.0	See desc column	

1155 (Supersedes BELAMS 003 TFF, which is obsolete)  
1 Jun 64

Army-Pf Portsmouth, N1-MON 1956-64

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
	5945-224-5782		AM-738/FRT-22 (continued) CONTACT, ELECTRICAL: Collins part/dwg #406-1100-00 Item Nos. K1621A (6 ea) K1613A (8 ea)			14	2.1	1.1	42.0		See desc column
	5945-283-6533		CONTACT, ELECTRICAL: Collins part/dwg #406-1900-00 Item Nos. K1612B(3 ea) K1613B(4 ea)			7	1.3	0.7	21.0		See desc column
	5945-259-6476		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0034-00			1	1.0	0.5	2.0		K1616A
	5945-259-6474		CONTACT, ELECTRICAL: Collins part/dwg #406-0035-00			1	1.0	0.5	3.0		K1616B
	5945-259-6475		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0024-00			1	1.0	0.5	2.0		K1621A
	5945-259-6472		CONTACT ASSEMBLY, ELECTRICAL: Collins part/dwg #406-0025-00			1	1.0	0.5	2.0		K1621B
O	5960-108-0252		ELECTRON TUBE: MIL type 3B28 Item Nos. V1613 thru V1616			4	35.2	17.6	400.0		See desc column
O	5960-188-0944		ELECTRON TUBE: MIL type 4B32 (OR) Item Nos. V1601 thru V1612			12	105.6	52.8	1200.0		See desc column
O	5960-188-8630		ELECTRON TUBE: MIL type 575A (OR item) Item Nos. V1601 thru V1612			12	105.6	52.8	1200.0		See desc column
P	4130-618-3285		FILTER, AIR CONDITIONING: Air Maze #00736			2	1.0	0.5	6.0		01601
O	5920-284-9220		FUSE, CARTRIDGE: MIL type FO2G1R00B Item Nos. F1601 thru F1607			7	2.1	1.1	350.0		See desc column
P	5920-570-5117		FUSEHOLDER: Buismen #HKF-Q-IR Item Nos. XF1601 thru XF1607			7	1.0	0.5	21.0		See desc column
P	5820-646-1983		INDICATOR, LOAD CURRENT AND ARC BACK: Dixon Electronics #PEC-A-132 Item Nos. TI609 thru TI620			12	1.3	0.7	36.0		See desc column
P	5970-144-1599		INSULATOR, BOWL: MIL type NS4W4601			24	1.0	0.5	24.0		E1616
P	5970-284-8427		INSULATOR, STANDOFF: MIL type NS4W0308			32	1.0	0.5	64.0		E1624
P	5970-117-5322		INSULATOR, STANDOFF: Collins part/dwg #503-8427-002			4	1.0	0.5	8.0		E1611

SELM5 Form  
1 Jun 64

1155 (Supersedes SELM5 003 TP, which is obsolete)  
AM-738/FRT-22



SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A B C D											
F	5970-117-5181		AM-738/FRT-22 (continued) INSULATOR, STANDOFF: MIL type #N84W0312			48	1.0	0.5	96.0		
F	5970-284-8166		INSULATOR, STANDOFF: MIL type NS4W0316			50	1.0	0.5	100.0		E1619
F	5970-284-8656		INSULATOR, STANDOFF: Collins part/dwg #190-1173-00			30	1.0	0.5	60.0		E1623
F	5970-284-4632		INSULATOR, STANDOFF: Collins part/dwg #190-1172-00			8	1.0	0.5	16.0		E1625
F	5970-151-8022		INSULATOR, STANDOFF: MIL type NS4W0324			8	1.0	0.5	16.0		E1626
F	5970-117-5325		INSULATOR, STANDOFF: Collins part/dwg #190-1176-00			6	1.0	0.5	12.0		E1627
F	5970-117-5189		INSULATOR, STANDOFF: Centralab #2X783			2	1.0	0.5	4.0		E1624
U	5355-667-9095		KNOB: Collins part/dwg #504-4617-002			2	1.0	0.5	6.0		E1633, E1634
O	5355-667-9236		KNOB: Collins part/dwg #502-9138-002			1	1.0	0.5	3.0		E1636
O	5355-667-9388		KNOB: Collins part/dwg #503-8168-003			1	1.0	0.5	3.0		E1635
F	6240-313-8980		LAMP, GLOW; Drake Mfg. #201001 Item Nos. 11610 thru 11616			7	2.1	1.1	350.0		See desc column
O	6240-143-3060		LAMP, INCANDESCENT: Collins part/dwg #262-0041-00 Item Nos. 11601 thru 11609			9	2.5	1.3	450.0		See desc column
O	6240-155-8706		LAMP, INCANDESCENT: GE #47 Item Nos. 11617 thru 11628			12	2.6	1.4	36.0		See desc column
F	6250-270-4260		LAMPHOLDER: Dialco #9-S-4634-L-46 Collins part/dwg #262-0042-00 Item Nos. 11601 thru 11603			3	1.0	0.5	15.0		See desc column
F	6210-299-3908		LENS, INDICATOR LIGHT: Collins part/dwg #262-0106-00			2	1.0	0.5	10.0		X11604A, X11607A
F	6210-299-3880		LENS, INDICATOR LIGHT: Collins part/dwg #262-0105-00			2	1.0	0.5	10.0		X11605A, X11609A

SELAS Form  
1 Jan 64

1155 (Successors SELAS 003 TP, which is obsolete)

AM-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A B C D			AM-738/FRT-22 (continued)								
F	6210-299-3882		LENS, INDICATOR LIGHT: Collins part/dwg #262-0104-00			2	1.0	0.5	10.0		X1606A, X1608A
F	6210-299-6381		LIGHT, INDICATOR: Dialco #51702-67 Item Nos. X1604 thru X1609			6	1.0	0.5	30.0		See desc column
F	6625-663-8107		METER, TIME, ELECTRIC: Weston #691			2	1.0	0.5	10.0		M1604, M1605
F	5950-519-6041		REACTOR: Thordarson #T-51355			1	1.0	0.5	2.0		L1602
F	5950-295-7813		REACTOR: Collins part/dwg #678-0365-00			1	1.0	0.5	2.0		L1601
F	5950-681-1740		REACTOR: Dixon Electronic #PEC-A-479 Item Nos. L1603 thru L1608			6	1.0	0.5	12.0		See desc column
F	5945-681-9941		RELAY, SOLENOID: A.B. #B-700			1	1.0	0.5	5.0		K1611
F	5945-502-9057		RELAY, SOLENOID: A.B. #Bal 702 Size 1			1	1.0	0.5	5.0		K1612
F	5945-258-4065		RELAY, SOLENOID: Collins part/dwg #405-0363-00			1	1.0	0.5	5.0		K1613
F	5945-665-7148		RELAY, SOLENOID: A.B. #B-200, Bal 700			2	1.0	0.5	10.0		K1616, K1623
F	5945-232-7708		RELAY, SOLENOID: A.B. #B-300, Bal 700			2	1.0	0.5	10.0		K1617, K1619
F	5945-259-6445		RELAY, SOLENOID: Collins part/dwg #405-0045-00			1	1.0	0.5	5.0		K1621
F	5945-259-6604		RELAY, MOTOR DRIVEN: Collins part/dwg #402-0054-00			1	1.0	0.5	5.0		K1614
F	5945-813-0609		RELAY, MOTOR DRIVEN: Collins part/dwg #402-0029-00			1	1.0	0.5	5.0		K1615
F	5945-577-1942		RELAY, THERMAL: Curtis Wright #117-5-A			1	1.0	0.5	5.0		K1622
F	5905-186-2968		RESISTOR, FIXED, COMPOSITION: MIL type RC428P471K			2	1.0	0.5	6.0		R1668 R1669
F	5905-279-4317		RESISTOR, FIXED, COMPOSITION: MIL type RC32GF184K			7	1.0	0.5	21.0		R1658 thru R1664

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
F	5905-249-4198		AM-738/FRT-22 (continued) RESISTOR, FIXED, COMPOSITION: MIL type RC42GF822K			2	1.0	0.5	6.0		R1670, R1671
F	5905-101-0743		RESISTOR, FIXED, WIRE WOUND: MIL type MFA-405			2	1.0	0.5	6.0		R1601, R1602
F	5905-306-2190		RESISTOR, FIXED, WIRE WOUND: GE #CR9033B1C23 Item Nos. R1646 thru R1657			12	1.3	0.7	36.0		See desc column
F	5905-309-5515		RESISTOR, FIXED, WIRE WOUND: GE #CR9033B5C45 Item Nos. R1620 thru R1623			4	1.0	0.5	12.0		See desc column
F	5905-542-8273		RESISTOR, FIXED, WIRE WOUND: MIL type RW10G3107 Item Nos. R1628 thru R1637			10	1.3	0.7	30.0		See desc column
F	5905-542-8218		RESISTOR, FIXED, WIRE WOUND: MIL type RW16G500 Item Nos. R1624 thru R1627			4	1.0	0.5	12.0		See desc column
F	5905-542-8208		RESISTOR, FIXED, WIRE WOUND: MIL type RW10G800 Item Nos. R1614 thru R1619			6	1.0	0.5	18.0		See desc column
F	5905-283-4739		RESISTOR, FIXED, WIRE WOUND: MIL type RW16G312 Item Nos. R1641 thru R1645			5	1.0	0.5	15.0		See desc column
F	5905-542-8206		RESISTOR, FIXED, WIRE WOUND: MIL type RW10G402 Item Nos. R1604 thru R1613			10	1.3	0.7	30.0		See desc column
F	5905-636-6696		RESISTOR, FIXED, WIRE WOUND: MIL type RW14G163			1	1.0	0.5	3.0		R1603
F	5905-231-9826		RESISTOR, VARIABLE: Collins part/dwg #749-7677-00			2	1.0	0.5	6.0		R1639, R1640
F	5905-636-6299		RESISTOR, VARIABLE: MIL type RP401FG500KK			1	1.0	0.5	3.0		R1638
F	5340-531-6811		RING, RETAINING: Collins part/dwg #340-0013-00			10	1.0	0.5	20.0		H1627
F	5935-204-6729		SOCKET, ELECTRON TUBE: MIL type TS-102C02			1	1.0	0.5	3.0		XK1622
F	5935-229-5670		SOCKET, ELECTRON TUBE: EF Johnson #123-211-22 Item Nos. XVi601 thru XVi612			12	1.3	0.7	36.0		See desc column

SELMS Form  
1 Jun 64

Army-Pt. Monmouth, NJ-MON 15

1155  
(Supersedes SELMS 003 TP, which is obsolete)  
AM-738/FRT-22

SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	1	C	D								
F	5935-129-3070		AM-738/FRT-22 (continued) SOCKET, ELECTRON TUBE: EF Johnson #123-209-51 Item No. XVI1613 thru XVI1616			4	1.0	0.5	12.0		See desc column
F	5930-224-5569		SWITCH, PUSH-PULL: GE #7460330-04 Item Nos. S1611, S1612, S1613			3	1.0	0.5	15.0		See desc column
F	5930-296-3916		SWITCH, LEVER: Collins part/dwg #503-8397-002			1	1.0	0.5	5.0		S1620
F	5930-201-5079		SWITCH, PUSH: C-H Bulletin 10250H			1	1.0	0.5	5.0		S1609
F	5930-296-6513		SWITCH, PUSH: Collins part/dwg #260-0352-00			1	1.0	0.5	5.0		S1610
F	5930-549-0533		SWITCH, ROTARY: Collins part/dwg #260-0855-00			1	1.0	0.5	5.0		S1608
F	5930-548-6453		SWITCH, ROTARY: Collins part/dwg #259-0314-00			1	1.0	0.5	5.0		S1621
F	5930-548-6133		SWITCH, ROTARY: Collins part/dwg #260-0354-00			1	1.0	0.5	5.0		S1622
F	5930-274-5116		SWITCH, TOGGLE: Collins part/dwg #260-0803-00			1	1.0	0.5	5.0		S1606
F	5940-270-2257		TERMINAL BOARD: Jones HB. #12-142 Item Nos. E1602 thru E1607, E1609, E1610			8	1.3	0.7	24.0		See desc column
F	5940-193-0217		TERMINAL BOARD: Jones HB #4-142			2	1.0	0.5	4.0		E1608, E1613
F	5950-251-7775		TRANSFORMER, POWER, STEP-DOWN: Collins part/dwg #672-0152-00 Item Nos. T1601 thru T1606			6	1.0	0.5	18.0		See desc column
F	5950-295-7250		TRANSFORMER, POWER, STEP-DOWN: Chi. Trans. #13094			1	1.0	0.5	3.0		T1607
F	5950-254-0037		TRANSFORMER, POWER, STEP-UP: Thordarson #7-51354			1	1.0	0.5	3.0		T1608
F	6625-649-2816		VOLTMETER: Weston #741-0 to 8.0	NX		1	1.0	0.5	4.0		M1601
F	6625-668-9312		VOLTMETER: Weston #744, 0-10 VAC	NX		1	1.0	0.5	4.0		M1603
F	6625-668-9316		VOLTMETER: Weston #744, 0-300 VAC			1	1.0	0.5	4.0		M1602

SELMS Form  
1 Jun 64

1155 (Supersedes SELMS 003 TF, which is obsolete)

AM-738/FRT-22

Amy-Ft Monmouth, NJ-JA00N 1950-64



SOURCE CODE	FEDERAL STOCK NUMBER	DESIGNATION BY MODEL	DESCRIPTION	UNIT OF ISSUE	EXP	QTY IN UNIT	DIRECT SUPPORT	GENERAL SUPPORT	DEPOT	ILLUSTRATION	
										FIGURE NO.	ITEM NO.
A	B	C	D								
			AM-738/FRT-22 (continued)								
			TRANSFORMER, POWER STEP-UP								
			TF-197/FRT-22 GROUP								
F	5920-810-9454		ARRESTER, LIGHTNING: Wemco #671-044			1	1.0	0.5	4.0		E1701
F	5977-321-9523		BRUSH ASSEMBLY, ELECTRICAL CONTACT: Imperial Electrical #BP1007			24	2.6	1.4	240.0		T1701B
F	6105-233-3195		MOTOR, ALTERNATING CURRENT: Superior Electric #58NY54HB1		NX	1					
F	5930-636-2886		SWITCH, SENSITIVE: Micro Switch #EZ-RWZ			4	1.0	0.5	5.0		S1701 thru S1704

SELM's Form 1155 (Supersedes SELM's 003 T.F., which is obsolete)  
1 Jun 64

AM-738/FRT-22

By Order of the Secretary of the Army:

HAROLD K. JOHNSON,  
General, United States Army,  
Chief of Staff.

Official:

J. C. LAMBERT,  
Major General, United States Army,  
The Adjutant General.

Distribution:

Active Army:

USASA (2)  
CNGB (1)  
OCC-E (7)  
CofT (1)  
CofEngrs (1)  
TSG (1)  
CofSptS (1)  
USAMC (5)  
USCONARC (5)  
ARADCOM (2)  
ARADCOM Rgn (2)  
OS Maj Comd (3)  
LOGCOMD (2)  
USAECOM (7)  
USAMICOM (4)  
USASMC (2)  
USASCC (4)  
USACDCCEA (1)  
USACDCCEA, Ft  
Monmouth (1)  
USAAVCOM (1)  
MDW (1)  
Armies (2)  
Corps (2)  
USAC (3)  
11th Air Assault  
Div (3)  
USATC AD (2)  
USATC Inf (2)  
USATC Armor (2)  
USATC Engr (2)  
USASTC (3)  
Svc Colleges (2)  
Br Svc Sch (2) except

Army Dep (2) except  
SAAD (30) LXAD, TOAD (14)  
FTWOAD (10) LEAD, NAAD,  
SVAD (5) SHAD, CHAD (3)  
ATAD (4)  
GENDEP (OS) (2)  
Sig Sec, GENDEP(OS) (5)  
Sig Dep (12)  
Instl (2) except Ft Monmouth (63)  
Ft Hancock (4) Ft Gordon (5)  
Ft Huachuca (10)  
Army Tml (1) except Oakland (5)  
POE (1)  
Sig Fld Maint Shops (2)  
WRAMC (1)  
US Army Pictorial Cen (2)  
Chicago Proc Dist (1)  
AMS (1)  
USAERDAA (2)  
USAERDAW (13)  
Units Org under fol TOE: (2 ea UNOINDC)  
11-16  
11-57  
11-97  
11-98  
11-117  
11-155  
11-157  
11-337  
11-500 AA-AE (4)  
11-557  
11-587  
11-592  
11-597

NG: None.

USAR: None.

For explanation of abbreviations used, see AR320-50.







TM 11-5820-235-35P

AMPLIFIER, RADIO FREQUENCY AM-738/FRT-22, AM-738A/FRT-22,  
AM-738B/FRT-22; CONTROL, POWER SUPPLY C-2446/FRT-22A; POWER  
SUPPLIES PP-1089/FRT-22, PP-1970/FRT-22A; TRANSFORMER, POWER,  
STEP-UP TF-197/FRT-22-1964